

400V STAR DELTA STARTER COMPONENT GUIDE

Riken

Main Contactor Delta Contactor Star Contactor Overload Relay Mech Interlock Timer Enclosure Isolator Ammeter

5.5 KW	RAB-A15T11-Q	RAB-A15T11-Q	RAB-1A5T11-Q	BTH-18TA2E8,0	RK-T352	ESDT1-Q	OK-2	JFD11-25A	AC72 0-20/40A
7.5 KW	RAB-A15T11-Q	RAB-A15T11-Q	RAB-A15T11-Q	BTH-18TA2E11	RK-T352	ESDT1-Q	OK-2	JFD11-25A	AC72 0-20/40A
11 KW	RAB-A15T11-Q	RAB-A15T11-Q	RAB-A15T11-Q	BTH-18TA2E13	RK-T352	ESDT1-Q	OK-2	JFD11-25A	AC72 0-30/60A
15 KW	RAB-A18T11-Q	RAB-A18T11-Q	RAB-A15T11-Q	BTH-18TA2E18	RK-T352	ESDT1-Q	OK-2	JFD11-40A	AC72 0-40/80A
18.5 KW	RAB-A25T11-Q	RAB-A25T11-Q	RAB-A18T11-Q	BTH-35TA2E26	RK-T352	ESDT1-Q	OK-3	JFD11-63A	AC72 0-60/5A
22 KW	RAB-A25T11-Q	RAB-A25T11-Q	RAB-A18T11-Q	BTH-35TA2E26	RK-T352	ESDT1-Q	OK-3	JFD11-63A	AC72 0-60/5A
30 KW	RAB-A35T11-Q	RAB-A35T11-Q	RAB-A25T11-Q	BTH-35TA2E36	RK-T352	ESDT1-Q	OK-3	JFD11-63A	AC72 0-75/5A
37 KW	RAB-A5011-Q	RAB-A50T11-Q	RAB-A25T11-Q	BTH-80T2E49	RK-T352	ESDT1-Q	FTE104	JFD11-100A	AC72 0-100/5A
45 KW	RAB-A65T11-Q	RAB-A65T11-Q	RAB-A35T11-Q	BTH-80T2E67	RK-T352	ESDT1-Q	FTE104	GGL-125/3J	AC72 0-100/5A
55 KW	RAB-A65T11-Q	RAB-A65T11-Q	RAB-A50T11-Q	BTH-80T2E67	RK-T352	ESDT1-Q	FTE104	GGL-160/3J	AC72 0-150/5A
75 KW	RAB-A80T11-Q	RAB-A80T11-Q	RAB-A65T11-Q	BTH-80T2E80	RL-800	ESDT1-Q	FTE105	GGL-160/3J	AC72 0-200/5A
90 KW	RAB-125T-Q	RAB-125T-Q	RAB-80T11-Q	BTH-125T2E128	RL-800	ESDT1-Q	FTE106	GGL-200/3J	AC72 0-250/5A
110 KW	RAB-150T-Q	RAB-150T-Q	RAB-80T11-Q	BTH-125T2E128	RL-800	ESDT1-Q	FTE106	GGL-250/3J	AC72 0-300/5A
132 KW	RAB-180T-Q	RAB-180T-Q	RAB-100T-Q	BTH-125T2E156	RL-800	ESDT1-Q	FTE106	GGL-250/3J	AC72 0-300/5A
160 KW	RAB-180T-Q	RAB-180T-Q	RAB-125T-Q	BTH-18T2E6,0 3 x 400:5A CT	RL-800	ESDT1-Q	FTE107	GGL-315/3J	AC72 0-400/5A
200 KW	RAB-260T-Q	RAB-260T-Q	RAB-150T-Q	BTH-18T2E6,0 3 x 500:5A CT	RL-800	ESDT1-Q	FTE107	GGL-400/3J	AC72 0-500/5A



Main Contactor Delta Contactor Star Contactor Overload Relay Mech Interlock Timer Enclosure Isolator Ammeter

5.5 KW	CE-D1210-Q	CE-D1210-Q	CE-D1210-Q	CE2-D138,0	CA9-D01	CEA-DT2	GW44218	JFD11-25A	AC48 0-20/40A
7.5 KW	CE-D1210-Q	CE-D1210-Q	CE-D1210-Q	CE2-D1310	CA9-D01	CEA-DT2	GW44218	JFD11-25A	AC48 0-20/40A
11 KW	CE-D1210-Q	CE-D1210-Q	CE-D1210-Q	CE2-D1313	CA9-D01	CEA-DT2	GW44218	JFD11-25A	AC48 0-30/60A
15 KW	CE-D1810-Q	CE-D1810-Q	CE-D1210-Q	CE2-D1318	CA9-D01	CEA-DT2	GW44218	JFD11-40A	AC48 0-40/80A
18.5 KW	CE-D2510-Q	CE-D2510-Q	CE-D1810-Q	CE2-D2332	CA9-D01	CEA-DT2	GW44219	JFD11-63A	AC72 0-60/5A
22 KW	CE-D2510-Q	CE-D2510-Q	CE-D1810-Q	CE2-D2332	CA9-D01	CEA-DT2	GW44219	JFD11-63A	AC72 0-60/5A
30 KW	CE-D3210-Q	CE-D3210-Q	CE-D2510-Q	CE2-D2332	CA9-D01	CEA-DT2	GW44219	JFD11-63A	AC72 0-75/5A
37 KW	CE-D4011-Q	CE-D4011-Q	CE-D2510-Q	CE2-D3340	CA9-D02	CEA-DT2	FTE104	JFD11-100A	AC72 0-100/5A
45 KW	CE-D5011-Q	CE-D5011-Q	CE-D3210-Q	CE2-D3350	CA9-D02	CEA-DT2	FTE104	GGL-125/3J	AC72 0-100/5A
55 KW	CE-D6511-Q	CE-D6511-Q	CE-D4011-Q	CE2-D3370	CA9-D02	CEA-DT2	FTE104	GGL-160/3J	AC72 0-150/5A
75 KW	CE-D8011-Q	CE-D8011-Q	CE-D5011-Q	CE2-D3380	CA9-D03	CEA-DT2	FTE105	GGL-160/3J	AC72 0-200/5A
90 KW	CE-F115-Q	CE-F115-Q	CE-D6511-Q	CE2-D62 120	N/A	CEA-DT2	FTE106	GGL-200/3J	AC72 0-250/5A
110 KW	CE-F150-Q	CE-F150-Q	CE-D8011-Q	CE2-D62 120	N/A	CEA-DT2	FTE106	GGL-250/3J	AC72 0-300/5A
132 KW	CE-F185-Q	CE-F185-Q	CE-D9511-Q	CE2-D62 150	N/A	CEA-DT2	FTE106	GGL-250/3J	AC72 0-300/5A
160 KW	CE-F185-Q	CE-F185-Q	CE-F115-Q	CE2-D62 180	N/A	CEA-DT2	FTE107	GGL-315/3J	AC72 0-400/5A
200 KW	CE-F265-Q	CE-F265-Q	CE-F150-Q	CE2-D66 250	N/A	CEA-DT2	FTE107	GGL-400/3J	AC72 0-500/5A